


## 7-way RV Travel Trailer Connector Wiring Color Code

#	Color	Gage	Circuit Function
1	white	10	common ground
2	blue	12	electric brake
3	green	14	tail/running lights
4	black	10	battery charge (+)
5	red	14	left turn/stop
6	brown	14	right turn/stop
7	yellow	14	auxiliary/back up



- NOTE: #7 is the center terminal and currently is most commonly used for backup lights.